

BLIND ANALOG TRANSMITTER Converts Pulse Frequency to 4 to 20 mA, Loop Powered







BAT-M shown installed on Series EFS2 meter. Meter sold separately.

The SERIES BAT Analog Transmitters is a 4 to 20 mA transmitter for use with the Series EFS2, IEFS, PDWS, PFT and FLMG.

FEATURES/BENEFITS

- · Easy to set up and can be either wall or meter mounted
- Takes a pulse frequency output from the compatible flow meters and converts it into a continuous 4 to 20 mÁ analog output signal
- The frequency for the flowmeter output signal can be adjusted using four rotary switches on the back of the transmitter and a microcontroller automatically scales all other values accordingly
- The microcontroller averages inputs for more stable reading outputs and is adjustable from 2 to 16 seconds
- · Loop powered, 2 wire connection

Description

· High environmental protection with semi-flexible urethane potted electrical components

APPLICATIONS

- · Telemetry applications
- Data logging ACCESSORIES

Model

· Distributed control systems

Chart recording

	with with the state of the sta
SPECIFICATIONS	
Input: Open-collector solid state sensor. Averaging: 2, 4, 8, 16 s (DIP switch	Response Time: 2 to (depends on input ave

3-5/8 [92.08]

(ତ)

 \odot

Input: Open-collector solid state sensor.	Response Time: 2 to 60 s; 90% FS
Averaging: 2, 4, 8, 16 s (DIP switch	(depends on input averaging).
selectable); Pulse Frequency: Min. 10	Loop Resistance: 0 to 1300 Ω max.0
Hz @ 20 mA; Max. 999.9 Hz (rotary DIP	Enclosure Material: Die-cast powder-
switch selectable).	coated aluminum.
Temperature Limits: 32 to 130°F (0 to	Enclosure Rating: NEMA 4X (IP66).
55°C).	Electrical Connections: Terminal block.
Output: 4 to 20 mA.	Mounting: See model chart.
Power Requirements: 24 to 36 VDC @	Weight: 3 lb (1361 g).
4 to 20 mA when loop powered.	···· g ······ (····· g)/

Œ

4-15/16 [125.44]

Duryer

PHONE 219-878-8000 FAX 219-872-99057

-3 [76.19]-

10.00

2-5/32

[54.92]

MODEL	MODEL CHART		
Model	Description		
BAT-M BAT-W	Blind analog transmitter, meter-mounted* Blind analog transmitter, wall-mounted		
*Compa	tible Series: EFS2, IEFS, PDWS, TBS and FLMG.		

OLoop Resistance: See Bulletin F-BAT