500X Series


All dimensions are nominal. Dimensions in [] are in millimeters.


How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code.

Sample Order Number: 500XB 45 02 L A 300 - FSL	Dial Size						
Optional Case Styles for 500X	4 ¹ /2"	6"	8 ¹ /2"	12"			
Flangeless, Black Finished, Cast Aluminum Case, Lower Connection	FSL	FSL	N/A	N/A			
Flangeless, Black Finished, Cast Aluminum Case, Back Connection	FSB	FSB	N/A	N/A			
Panel Mounted, Hinged Ring Case Back Connection	HRB	HRB	N/A	HRB			
Panel Mounted, Hinged Ring Case Lower Connection	HRL	HRL	N/A	HRL			

N/A = Not available. Please order using the code listed.


Flangeless







Dial Size	C	E	F	G	Н	J
41/2"	4.79 [121.7]	3.83 [97.2]	0.94 [23.8]	1.63 [41.3]	1.46 [37.1]	2.00 [50.8]
6"	6.29 [159.8]	4.70 [119.5]	0.94 [23.8]	1.63 [41.3]	1.46 [37.1]	2.03 [51.6]

Hinged Ring







Dial Size	C	G	Н	J	K	L	М	N	P
41/2"	6.10 [155]	1.62 [41]	1.59 [40]	1.97 [50]	5.38 [136]	0.22 [5]	4.78 [121]	4.94 [125]	0.34 [8]
6"	7.69 [195]	1.62 [41]	1.59 [40]	1.97 [50]	7.00 [177]	0.28 [7]	6.22 [158]	6.44 [163]	0.34 [8]
12"	14.75 [375]	1.62 [41]	1.38 [35]	2.50 [63.5]	13.50 [342]	0.28 [7]	12.50 [317]	12.81 [325]	0.73 [18.5]


Optional Case Styles 600C

All dimensions are nominal. Dimensions in [] are in millimeters.


Kit Only. Not Factory installed.	Dia	al Size
Optional Case Style - 600C	3 1/2"	41/2"
Surface Mounted Back Flange Kit	198-0023	198-0016

Please order using the code listed.

31/2" Includes back flange. Use existing screws from gauge.



4¹/₂" Includes back flange and replacement screws.



700 Series


All dimensions are nominal. Dimensions in [] are in millimeters.


How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code.

Sample Order Number: 700SS 40 04 B D 300 - FMB		DIAL SIZE					
Case Style - 700 Series	2 ¹ /2"	4"	6"				
Surface Mounted Case with Back Flange, Lower Connection	SML	SML	SML				
Surface Mounted Case with Back Flange, Back Connection	SMB	SMB	SMB				
Flush Mounted Case with Front Flange, Back Connection	FMB	FMB	FMB				
Flush Mounted Case with Front Flange, Lower Connection	N/A	FML	FML				
Panel Mounted Case with U-Clamp, Back Connection	UCB	UCB	UCB				

N/A = Not available. Please order using the code listed.


2 1/2", 4" & 6" Surface Mount





Dial Size	Material	A	C	D	E	F	G	Н	J	K	P
21/2" [63]	Brass	3.35 [85]	2.52 [64]	0.14 [3.6]	2.22 [56.5]	0.57 [14.5]	0 [0]	0.98 [25]	1.56 [39.5]	2.95 [75]	0.22 [5.5]
	SS	3.35 [85]	2.52 [64]	0.14 [3.6]	2.22 [56.5]	0.57 [14.5]	0 [0]	0.98 [25]	1.56 [39.5]	2.95 [75]	0.22 [5.5]
4" [100]	Brass	5.20 [132]	3.98 [101]	0.19 [5]	3.39 [86]	0.75 [19]	1.04 [27]	1.32 [34]	2.07 [53]	4.57 [116]	0.22 [5.5]
	SS	5.20 [132]	3.98 [101]	0.19 [5]	3.39 [86]	0.75 [19]	1.36 [35]	1.26 [32]	2.07 [53]	4.57 [116]	0.22 [5.5]
6" [150]	Brass	7.72 [196]	6.34 [161]	0.23 [6]	4.57 [116]	0.81 [21]	1.04 [27]	1.32 [34]	2.09 [53]	7.01 [178]	0.24 [6]
	SS	7.72 [196]	6.34 [161]	0.23 [6]	4.57 [116]	0.81 [21]	1.36 [35]	1.26 [32]	2.09 [53]	7.01 [178]	0.24 [6]

21/2" Front Flange






All dimensions are nominal. Dimensions in [] are in millimeters.


700 Series


4" & 6" Front Flange



	Dial Size	Material	A	C	D	E	F	G	Н	J	K	N	P
ı	4" [100]	Brass	5.20 [132]	3.98 [101]	0.19 [5]	3.39 [86]	0.63 [16]	1.04 [27]	1.44 [37]	1.93 [49]	4.57 [116]	4.13 [105]	0.24 [6]
		SS	5.20 [132]	3.98 [101]	0.19 [5]	3.39 [86]	0.63 [16]	1.36 [35]	1.38 [35]	1.93 [49]	4.57 [116]	4.13 [105]	0.24 [6]
Ī	6" [150]	Brass	7.72 [196]	6.34 [161]	0.23 [6]	4.57 [116]	0.69 [18]	1.04 [27]	1.44 [37]	1.97 [50]	7.01 [178]	6.50 [165]	0.24 [6]
		SS	7.72 [196]	6.34 [161]	0.23 [6]	4.57 [116]	0.69 [18]	1.36 [35]	1.38 [35]	1.97 [50]	7.01 [178]	6.50 [165]	0.24 [6]


21/2" U-Clamp





4" & 6" U-Clamp





Dial Size	Material	A	C	G	Н	J	N	P
4" [100]	Brass	4.33 [110]	3.98 [101]	1.04 [27]	1.44 [37]	1.93 [49]	4.02 [102]	0.18 [5]
	SS	4.33 [110]	3.98 [101]	1.36 [35]	1.38 [35]	1.93 [49]	4.02 [102]	0.18 [5]
6" [150]	Brass	6.69 [170]	6.34 [161]	1.04 [27]	1.44 [37]	1.97 [50]	6.39 [162]	0.24 [6]
	SS	6.69 [170]	6.34 [161]	1.36 [35]	1.38 [35]	1.97 [50]	6.39 [162]	0.24 [6]

760B, 765B & 766SS


All dimensions are nominal. Dimensions in [] are in millimeters.

How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code.

Sample Order Number: 766SS 60 02 L M 660 - SML	760B	760B	765B/766SS	765B/766SS	765B/766SS
Optional Case Styles for 760B, 765B & 766SS	2 1/2"	4"	2.5"	4"	6"
Surface Mounted Case with Back Flange, Lower Connection	N/A	N/A	N/A	SML	SML
Surface Mounted Case with Back Flange, Back Connection	N/A	N/A	N/A	SMB	SMB
Flush Mounted Case with Front Flange, Back Connection	FMB	FMB	N/A	FMB	FMB
Flush Mounted Case with Front Flange, Lower Connection	N/A	N/A	N/A	FML	FML
Panel Mounted Case with U-Clamp, Back Connection	UCB*	N/A	UCB	UCB	UCB


N/A = Not available. Please order using the code listed.

765B & 766SS 4" & 6" Surface Mount



Dial Size	A	C	D	E	F	Н	J	K	P
4" [100]	5.20 [132]	3.98 [101]	0.19 [5]	3.43 [87]	0.75 [19]	1.26 [32]	2.07 [53]	4.57 [116]	0.22 [5.5]
6" [150]	7.72 [196]	6.34 [161]	0.23 [6]	4.84 [123]	0.81 [21]	1.26 [32]	2.09 [53]	7.01 [178]	0.22 [5.5]


760B 21/2" Front Flange




^{*}Supplied with stainless steel case.

760B, 765B & 766SS

All dimensions are nominal. Dimensions in [] are in millimeters.



Dial Size	Material	A	C	D	E	F	H	J	K	N	Р
4" [100]	Brass	5.20 [132]	3.98 [101]	0.19 [5]	3.43 [87]	0.63 [16]	1.38 [35]	1.93 [49]	4.57 [116]	4.13 [105]	0.24 [6]
	SS	5.20 [132]	3.98 [101]	0.19 [5]	3.43 [87]	0.63 [16]	1.38 [35]	1.93 [49]	4.57 [116]	4.13 [105]	0.24 [6]
6" [150]	Brass	7.72 [196]	6.34 [161]	0.23 [6]	4.76 [121]	0.69 [18]	1.38 [35]	1.97 [50]	7.01 [178]	6.50 [165]	0.24 [6]
	SS	7.72 [196]	6.34 [161]	0.23 [6]	4.84 [123]	0.69 [18]	1.38 [35]	1.97 [50]	7.01 [178]	6.50 [165]	0.24 [6]





D80 Series

All dimensions are nominal. Dimensions in [] are in millimeters.


How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code.

Sample Order Number: D82LFB 25 02 L A 300 - SML

	Dial Size					
Case Style - D80 Series	2"	21/2"	4"			
Surface Mounted, Back Flange Case for Lower Connection	N/A	SML	SML			
* Panel Mounted, Front Flange Kit for Back Connection	198-0028	198-0025	FMB			
* Panel Mounted, Front Ring Kit for Back Connection	N/A	198-0024	N/A			
Panel Mounted, U-Clamp Kit for Back Connection	034-0036	034-0037	UCB			


^{*} Kit Only. Not Factory installed.

21/2" & 4" Surface Mount



Dial S	Size	A	В	C	D	E	F	J	K
21/2"	'	3.35 [85]	1.43 [36.3]	2.68 [68]	0.14 [3.6]	2.23 [56.6]	0.52 [13.2]	1.38 [35.1]	2.95 [75]
4"		5.20 [132]	2.19 [55.6]	4.18 [106]	0.19 [4.8]	3.07 [78]	0.62 [15.7]	1.47 [37.3]	4.57 [116]

2", 21/2" & 4" Front Flange




Dial Size	A	C	Н	J	K	P
2"	3.03 [77]	2.09 [53]	0.99 [25]	0.94 [24]	2.65 [65]	0.32 [8]
21/2"	3.35 [85]	2.67 [68]	0.99 [25]	0.82 [21]	2.95 [75]	0.32 [8]
4"	5.20 [132]	4.17 [106]	0.99 [25]	0.91 [23]	4.56 [116]	0.42 [10]


All dimensions are nominal. Dimensions in [] are in millimeters.

D80 Series

21/2" Front Ring



2", 21/2" & 4" U-Clamp



Dial Size	C	Н	J	М	P	R	V
2"	2.09 [53]	0.99 [25]	1.10 [28]	1.91 [48.5]	0.18 [4.5]	2.28 [58]	2.76 [70]
21/2"	2.68 [68]	0.99 [25]	1.20 [30.5]	2.44 [62]	0.28 [7]	2.83 [72]	3.31 [84]
4"	4.17 [106]	0.99 [25]	1.32 [33.5]	3.88 [98.6]	0.28 [7]	4.33 [110]	4.80 [122]

800 Series

All dimensions are nominal. Dimensions in [] are in millimeters.

How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code.

Sample Order Number: 800B 15 01 B D 300 - UCB


	Dial Size				
Case Styles - 800 Series	11/2"	2"	2 ¹ /2"	4"	
Panel Mounted Case with Front Flange, Back Connection	FMB	FMB	FMB	FMB	
Panel Mounted Case with U-Clamp, Back Connection	UCB	UCB	UCB	N/A	


Please order using the code listed.

Front Flange L-3 HOLES EQUALLY SPACED .22 [5.5] H C [14] A.F.

Dial Size	C	Н	J	К	L	М
11/2"	2.40 [61]	0.73 [18.5]	0.98 [25]	1.97 [50]	0.14 [3.5]	1.61 [41]
2"	2.80 [71]	0.83 [21]	1.02 [26]	2.36 [60]	0.14 [3.5]	1.97 [50]
21/2"	3.35 [85]	0.83 [21]	1.06 [27]	2.95 [75]	0.14 [3.5]	2.52 [64]
4"	5.20 [132]	0.98 [25]	1.26 [32]	4.57 [116]	0.19 [4.8]	3.96 [100.5]

11/2", 2", 21/2" U-Clamp





Dial Size	C	H	J	N	P	R	V
11/2"	1.73 [44]	1.08 [27.5]	1.12 [28.5]	1.57 [40]	0.24 [6]	1.97 [50]	2.44 [62]
2"	2.13 [54]	1.02 [26]	1.18 [30]	1.97 [50]	0.22 [5.5]	2.28 [58]	2.76 [70]
21/2"	2.68 [68]	1.02 [26]	1.18 [30]	2.48 [63]	0.22 [5.5]	2.83 [72]	3.31 [84]

800LF Series

All dimensions are nominal. Dimensions in [] are in millimeters.


How to Order: Specify the Optional Case Code at the end of the Instrument Ordering Code. *Sample Order Number:* **800LFB 35 02 B A 300 - UCB**

	Dial Size		
Case Styles - 800LF Series	2 1/2"	31/2"	
* Panel Mounted, Front Flange Kit for Back Connection	198-0020	N/A	
* Surface Mounted, Back Flange Kit for Lower Connection	198-0022	N/A	
* Panel Mounted, Front Ring Kit for Back Connection	198-0021	N/A	
* Panel Mounted, U-Clamp Kit for Back Connection	198-0026	N/A	
Panel Mounted Case with U-Clamp, Back Connection	N/A	UCB	


^{*} Kit Only. Not Factory installed.

Please order using the code listed.

2¹/₂" Front Flange




21/2" Back Flange





800LF Series (continued)

All dimensions are nominal. Dimensions in [] are in millimeters.


21/2" Front Ring








21/2" U-Clamp





31/2" U-Clamp



