
MZ20 -8905



## **Cleaning system**



Type MZ20 can be combined with...



Online Analysis System

The Cleaning Module MZ20 and the Control Module ME24 are fully compatible to type 8905 systems.

The Cleaning System is designed to clean the fluidic channels and in case the sensor area in the connected sensor cubes using up to two cleaning liquids. The cleaning is proceeded fully automatically. When a cleaning is requested e.g. by a timer within the Control Module, all necessary steps are started. Sample water stop ightarrow dosing of cleaning liquid ightarrow duration when cleaning is active  $\rightarrow$  flush system  $\rightarrow$  in case: dose next cleaning solution  $\rightarrow$  a.s.o. All timers and criteria are user defined and this allows optimized adjustment to the cleaning demand. The cleaning parameters might be set via 7" touch display at the 8905 Online-Analysis-System or by a Bürkert Communicator. Using the automatic cleaning system allows reducing the manual cleaning of the sensors and improve the long term stability of the measurements. The cleaning system operates without maintenance except the change of empty tanks by new filled cleaning solutions.

- Automatic cleaning for type MSxx sensor cubes
- Protection against clogging in the system and inside the sensor cubes for long time accurate measurements
- Two cleaning liquids for specific cleaning procedures
- Application specific programmable cleaning cycle

General data	
Compatibility	with Online Analysis System Type 8905
	(see corresponding data sheet)
Used valves	Type 0331 and Type 0127
Materials	
Housing	PC (anthracite, UV stabilized, UL94 V0)
Base block	PA 6C (black)
Seal	EPDM
Fluidics	PP, aluminium
Fluidic connection	Stainless steel
Cable glands	TPE (black)
Type of medium	Water without particles: drinking water, industrial water Chemicals: all Bürkert approved and released cleaning solution
Sample water temperature	<b>340°C</b> (37104°F)
Sample water pressure	PN3
Weight	1.3 kg (with additional modules in the minimum configuration)
Electrical data	
Operating voltage	24 V DC $\pm 10\%$ through the backplane of the system Type 8095 via büS or external power supply
Power consumption	14 VA
Internal communication	through büS (Bürkert bus)
Environment	
Ambient temperature	
Operating	0+40°C (-4104°F)
Storage	-20+70°C (-4158°F)
Relative humidity	< 95%, without condensation
Max. height above sea level	max. 2000 m


MZ20 -8905



Standards, directives and approvals	
Protection class acc. to EN 60529 MZ20 Cleaning module alone Cleaning System for 8905 consisting of MZ20, 3 x BEF1, 2 x ME29 and ME24	IP20 IP65
Standard and directives EMC Approvals	EN 61000-6-4 CE, UL pending

#### Design and principle of operation

The sample water flows through the cleaning system and then into the online analysis system. Depending on the configuration 1 up to 2 connections for cleaning agents are available. During a cleaning cycle the sample water flow is interrupted and detergent will be circulated into the online analysis system. After the expiration of the programmed contact time, the sample water flow is released again.




### Installation



The cleaning system has to be placed before the Online Analysis System Type 8905. It is mounted on a DIN rail according to EN 50022.

The fluid outlet of the cleaning system has to be connected to the fluid inlet of the Online Analysis System. As well the electrical connection has to be carried out.


The cleaning system must be connected to the büS through a relevant wiring. Depending on its position on the büS, it should or not be provided with a terminating resistor of 120 Ohm.





burkert

# Dimensions [mm]



### Ordering chart - Cleaning system Type MZ20

Description	ltem no.
Cleaning system, 2 solutions	567 124

### Ordering chart - accessories and spare parts

Description	ltem no.
Cleaning solution	
Acidic, 250 ml	807 478
Acidic, 1000 ml	807 479
Acidic, 5000 ml	807 480
Basic, 250 ml	807 486
Basic, 1000 ml	807 487
Basic, 5000 ml	807 489

MZ20 -8905



#### Ordering chart - accessories and spare parts, continued

bus cable extension, straight male connector/straight female connector, 3 m7bus cable extension, straight male connector/straight female connector, 5 m7bus cable extension, free end/straight female connector, 1 m7bus cable extension, free end/straight female connector, 3 m7bus cable extension, free end/straight female connector, 3 m7bus cable extension, free end/straight female connector, 5 m7bus male connector M12, angled7bus Y-junction7bus Y-junction with voltage interruption7USB-bus-Interface (see drawing below)7	72 404 72 405 72 406 72 409
bus cable extension, straight male connector/straight female connector, 3 m7bus cable extension, straight male connector/straight female connector, 5 m7bus cable extension, free end/straight female connector, 1 m7bus cable extension, free end/straight female connector, 3 m7bus cable extension, free end/straight female connector, 3 m7bus cable extension, free end/straight female connector, 5 m7bus cable extension, free end/straight female connector, 5 m7bus cable extension, free end/straight female connector, 5 m7bus male connector M12, angled7bus Y-junction7bus Y-junction with voltage interruption7USB-bus-Interface (see drawing below)7	72 405 72 406 72 409
büS cable extension, straight male connector/straight female connector, 5 m7büS cable extension, free end/straight female connector, 1 m77büS cable extension, free end/straight female connector, 3 m77büS cable extension, free end/straight female connector, 5 m77büS male connector M12, angled77büS Y-junction77büS Y-junction with voltage interruption77USB-büS-Interface (see drawing below)77	72 406 72 409
büß cable extension, free end/straight female connector, 1 m   77     büß cable extension, free end/straight female connector, 3 m   77     büß cable extension, free end/straight female connector, 5 m   77     büß male connector M12, angled   77     büß Y-junction   77     büß Y-junction with voltage interruption   77     USB-büß-Interface (see drawing below)   77	72 409
büß cable extension, free end/straight female connector, 3 m   7     büß cable extension, free end/straight female connector, 5 m   7     büß male connector M12, angled   7     büß Y-junction   7     büß Y-junction with voltage interruption   7     USB-büß-Interface (see drawing below)   7	
büS cable extension, free end/straight female connector, 5 m   7     büS male connector M12, angled   7     büS Y-junction   7     büS Y-junction with voltage interruption   7     USB-büS-Interface (see drawing below)   7	70 410
büS male connector M12, angled 7   büS Y-junction 7   büS Y-junction with voltage interruption 7   USB-büS-Interface (see drawing below) 7	72 410
büs Y-junction 7   büs Y-junction with voltage interruption 7   USB-büS-Interface (see drawing below) 7	72 411
büS Y-junction with voltage interruption 7   USB-büS-Interface (see drawing below) 7	72 419
USB-büS-Interface (see drawing below) 7	72 420
	72 421
	72 426
USB-büS-Interface, Stick and cable 7	72 551
Other installation materials	
Sample-water pipe 4/6 mm, 5 m 5	67 793
Sample-water pipe 4/6 mm, 10 m 5	67 701
Sample-water pipe 4/6 mm, 25 m 5	67 794
Set with a pressure reducer (including a 100 µm strainer, a sampling point and two G1/4" connections), a wall-mounting bracket with nut (for the pressure reducer), a pressure gauge (for the pressure reducer) and two quick-connect couplings	66 319



EDIP

To find your nearest Bürkert facility, click on the orange box ightarrow

www.burkert.com

In case of special application conditions, please consult for advice.

Subject to alteration. © Christian Bürkert GmbH & Co. KG

1705/2\_EU-en\_00895293